

12-24V PSU for Hub 2/Hub 2 Plus/ReX 2

[Where to buy](#)

Tech specs

12-24V PSU for Hub 2/Hub 2 Plus/ReX 2

Power supply unit for the device operation from a low-voltage power source



Compatibility

Hubs

Hub 2 (2G) >

Hub 2 (4G) >

Hub 2 Plus >

Radio signal range extenders

ReX 2 >

Input

Voltage

8–32 V $\overline{=}$

Current

up to 1 A

Turn-on voltage

8 V $\overline{=}$ $\pm$ 2.5%

Turn-off voltage

7–7.5 V $\overline{=}$

Depends on the load

Output

Voltage

4.8 V $\overline{=}$ $\pm$ 5%

Current

up to 1.5 A

Installation

Installation method

into the hub or range extender enclosure by replacing the bundled power supply board

Operating temperature range

from -10°C to +40°C

Operating humidity

up to 75%



Connection to the power supply network

Connector slot

6.5 × 2 mm

Power jack (female)

Connector

5.5 × 2.1 mm

Power jack (male)

Board

Colour

N/A

Dimensions

98 × 70 × 17 mm

Weight

26 g

Complete set

12–24V PSU for Hub 2/Hub 2 Plus/ReX 2

Terminal adapter

Quick start guide

Additional information

Compliance with standards

[Learn more](#) >

Warranty

24 months

[Learn more](#) >

User manual

[Learn more](#) >

Subscribe

Subscribe to our emails about secure life. No spam.

[Subscribe](#)

Request extra help

✉ support@ajax.systems

📍 @AjaxSystemsSupport_Bot



Products

Superior

Fibra

Intrusion protection

Fire detection

Water leak prevention

Comfort & Productivity

Solutions

Why Ajax

How it works

Scenarios

Customer stories

Reviews and feedback

Company

Blog

About us

Newsroom

Events

Career

Software

For users

PRO Desktop

Ajax Translator

Scenarios



Support

Manuals and articles

Compliance with standards

Tools

Battery life calculator

Jeweller range calculator

Fibra power supply calculator

Light switches configurator

For partners

Business with Ajax

Events

Brandbook

Enterprise API

CMS integration

